

SIMATIC S7-300, Simulator module SM 374, for simulation of 16 inputs or 16 outputs or 8 inputs and 8 outputs 16 switches, 16 LEDs



Input current		
from backplane bus 5 V DC, max.		80 mA
Power loss		
Power loss, typ.		0.35 W
Digital inputs		
Number of digital inputs		16; Switch
Digital outputs		
Number of digital outputs		16; LEDs
Analog inputs		
Number of analog inputs		0
Analog outputs		
Number of analog outputs		0
Potential separation		
Potential separation digital inputs		
• between the channels and backplane bus		No
Potential separation digital outputs		

- between the channels and backplane bus

No

Dimensions

Width	40 mm
Height	125 mm
Depth	120 mm

Weights

Weight, approx.	190 g
-----------------	-------

last modified: 12/24/2018